

<b>MODEL</b>	<b>Cinénova Grande</b>
<b>Number of Channels</b>	5-channels / 7-channels
<b>Power Rating Per Channel</b>	<sup>1</sup> (8-ohm load), all channels driven: 360 Watts <sup>2</sup> (4-ohm load), all channels driven: 610 Watts <sup>2</sup> (2-ohm load), all channels driven: 810 Watts
<b>Output Load Impedance</b>	Safe with all loads from 2-Ohm to 16-Ohm
<b>Input Impedance</b>	- RCA: 28-kOhms - XLR: 48-kOhms
<b>Input Sensitivity</b>	- RCA: 1.6V - XLR: 2.4V
<b>Voltage Gain (Av)</b>	42V Gain Relative to 1 watt
<b>Frequency Response</b>	up to 50kHz ±0.1dB
<b>Crossover Filter (low-pass/high-pass)</b>	Variable Selector from 20Hz - 5kHz with a slope of 12dB/Octave
<b>Total Harmonic Distortion + Noise</b>	0.003% at 1 watt
<b>Signal to Noise Ratio (A-Weighted)</b>	Greater than -121 dB
<b>Cross Talk / Channel Separation</b>	Greater than -110 dB from 17Hz to 40kHz
<b>Slew Rate</b>	55V/microsecond
<b>Damping Factor</b>	1600 at 8-Ohm, 800 at 4-Ohm, 400 at 2-Ohm
<b>DC Output Offset</b>	Less than 0.004V
<b>Power Requirement</b>	120 VAC/240 VAC Factory Pre-set
<b>Chassis Dimensions (H x W x D)</b>	9 1/4" x 18" x 21" (235mm)x(457mm)x(533mm)
<b>Net Weight</b>	<b>Cinénova-5:</b> 110 pounds / 49.9Kg <b>Cinénova-7:</b> 122 pounds / 55.3Kg
<b>Shipping Weight</b>	<b>Cinénova-5:</b> 134 pounds / 60.8Kg <b>Cinénova-7:</b> 148 pounds / 67.1Kg

<sup>1</sup> RMS power, measured at 1% THD and 1kHz input frequency

<sup>2</sup> Adequate ventilation may be required and 240VAC/20 Ampere circuit is recommended