



## AXA35

Integrated Stereo Amplifier with (Built-in) Phono-Stage



## Sound Comes First

Our AXA35 integrated amp offers 35 watts per channel and has a built-in moving magnet phono stage – perfect for vinyl enthusiasts.

A white LED dot matrix display confirms listening source, and separate tone controls mean you can adjust the sound to suit your taste.

There's a large ¼" (6.35mm) headphone socket too, ideal for high-quality listening without disturbing those who might not share your great taste in music.

## Highlights

- **35 Watts Power per Channel** – for detailed performance at all volumes
- **Built-In Phono Stage** – to plug & play a vinyl turntable
- **Slim Timeless Design** – classic hi-fi size, with Lunar Grey aluminium trim
- **Tone Controls** – fine-tune sound to compensate for room dynamics
- **Digital Display** – white LED, clearly shows; source, volume & menus
- **Headphone Socket** – full size socket for high-quality after-hours listening
- **Front Aux Input** – 3.5mm socket to easily connect compatible devices

## Specification

POWER OUTPUT	35 Watts (into 8 Ohms)
THD (UNWEIGHTED)	<0.01% @ 1kHz, 80% of rated power <0.15% 20Hz – 20kHz, 80% of rated power
FREQUENCY RESPONSE (-3DB)	5Hz - 50kHz
S/N RATIO (REF 1W)	>82dB (unweighted)
INPUT IMPEDANCES	47k ohms
POWER AMP DAMPING FACTOR	>50
MAX. POWER CONSUMPTION	260W
BASS/TREBLE CONTROLS	Shelving, ultimate boost/cut +/- 10dB @ 100Hz and 10kHz
STANDBY POWER CONSUMPTION	<0.5W
INPUTS	4x RCA, 1x Phono, 1 x 3.5mm Aux input (front panel)
OUTPUTS	Speakers, Rec Out, USB 5V power
DIMENSIONS (WXHxD)	430 x 83 x 335mm (16.9 x 3.3 x 13.2")
WEIGHT	5.6kg (12.3lbs)
IN THE BOX	AXA35 Integrated Amplifier, Power Cable, Remote Control, 2 x AAA Batteries